

marantz®



SR7008

AV RECEIVER



Building on the strengths of the SR7007, the new SR7008 extends the number of channels from seven to nine. That's right, this new receiver can drive nine separate speakers, each with 200W of pure power. And because this muscle-pack is supported by Audyssey DSX and DTS Neo:X 9.1 you are flooded with the ultimate experience in surround sound. We have also upgraded Audyssey to MultEQ XT32 /LFC Pro so you get an even more accurate calibration of the speaker and guarantee that every seat in the room is a 'sweet spot' for audio. And because the set also supports Apple lossless, Gapless, and FLAC HD 192/24 network streaming you also get all the metadata you want as well as music services such as Spotify and last.fm and AirPlay audio streaming.

But we haven't changed everything. For example, the stylish aluminium front panel with illuminated porthole display is still there. We've also kept the staggering impact of audio quality, which is quite simply an intoxicating mix of effortless power, amazing detail and sensational depth: all thanks to the use of current feedback technology, HDAM pre-amplification and, of course the 200W for each of the nine channels. You can enjoy this superior audio performance for all your music and movie sources. Video signals are treated with extra loving care via advanced video processing, and 6+1 HDMI inputs, and 2+1 outputs (Dual output for main zone & Multi Zone output), all of which support 3D 4k pass-through and 4k scaling video. The front digital connectivity (HDMI & USB) makes it particularly friendly for mobile, tablet, iPad/iPhone, camera & camcorder. What's more, the front panel folds up to reveal an additional two-line display. And to get it all up and running effortlessly, there's also Setup Assistant. Enough said?

green standby
eco friendly

HDAM

dts
Neo:X | 9.1

HDMI 6+1 in
3 out

4K HD
VIDEO

PC AUDIO
STREAMING

Spotify

AirPlay

Windows 8
Windows RT
Compatible

Main Features

- 9ch discrete power amplifier, 200 W per channel
- Current Feedback circuitry with Marantz HDAM
- 9.2 signal processing and Clock Jitter Reducer
- DLNA1.5 Network audio streaming and Internet radio
- MP3, WAV, AAC, FLAC, WMA, Lossless, FLAC192/24 (HD)
- Gapless Playback
- Spotify*, last.fm*, Flickr, Internet Radio support
- Apple AirPlay and Windows 8/RT compatible
- Audyssey MultEQ XT32, LFC, Dynamic EQ and Dynamic Volume
- DTS Neo:X (up to 9.1) and Audyssey DSX Processing
- 6+1in HDMI (3D/ARC/CEC/4K), 2+1out, HDMI output for Zone2
- Full 4k compatibility – Scaling – Pass through – GUI overlay
- Analogue & HDMI Upconversion to 4k
- InstaPrevue, to preview HDMI input sources on screen
- Multilingual Setup Assistant and Audyssey calibration makes hook up an easy task
- Multi room/Multi source (3 Zones)
- Zone output from 2-channel digital PCM sources (coaxial, optical, HDMI, network)
- 11.2 Preout (with 2 independent subwoofers), Phono MM amplifier
- New Marantz Remote App for iOS and Android devices

EAN

EU	SR7008/N1B	4951035050675	Black
	SR7008/N1SG	4951035050668	Silver-Gold
UK	SR7008/T1B	4951035050675	Black
	SR7008/T1SG	4951035050668	Silver-Gold

www.marantz.eu



because music matters

SR7008

AV RECEIVER



FEATURES	SR7008
MULTICHANNEL SURROUND	
DTS HD Master / DTS 5.1 / DTS ES / DTS 96/24	• / • / • / •
Dolby Digital Plus / Dolby TrueHD / Dolby Digital EX / DPL IIz	• / • / • / •
Audyssey DSX	•
DTS Neo:X	• (up to 9.1)
Multichannel Stereo	•
Compressed audio Enhancer: MDAX2	•
NETWORK	
DLNA Certified	• (v1.5)
Lossy formats MP3 / WMA / AAC	• / • / •
Lossless formats FLAC / ALAC / WAV	• / • / •
FLAC HD 192/24	•
WAV 192/24	•
ALAC 96/24	•
Gapless playback	• (FLAC, WAV)
Photo streaming (JPEG)	•
AirPlay audio streaming	•
Windows 8/RT compatible	• / •
Internet Radio (vTuner)	•
Spotify*	•
last.fm*	•
Compatible with Remote APP for Smart Phones	Android/iOS
Ethernet	•
OTHERS	
Bluetooth audio via RX101	optional
Current Feedback Topology	•
Hyper Dynamic Amplifier Modules (HDAM)	•
Auto speaker setup by microphone	Audyssey MultEQ XT32 (Pro)
Audyssey LFC	•
Audyssey Dynamic EQ / Dynamic Volume	• / •
Video conversion CVBS > HDMI; Comp > HDMI	•
Analogue to HDMI scaling	up to 4k
HDMI to HDMI scaling	up to 4k
HDMI InstaPrevue	•
Video processing	•
Picture adjust / Noise reduction	• / •
HDMI path through on stand-by	•
4k video pass through	•
3D video pass through	•
Audio Return Channel	•
On Screen Display: Advanced GUI	•
GUI overlay on HDMI	•
Setup Assistant (English, German, French, Spanish, Italian, Dutch, Swedish, Polish, Russian)	•
Variable cross over	•
Optimized Bass Redirection	•
Multiroom zones	2 (incl. HDMI)
Zone output from 2-channel digital PCM sources (coaxial, optical, HDMI, network)	•

INPUTS/OUTPUTS	
VIDEO	
Composite In / Out	3+1 / 3 (incl. Zone2)
Component In / Out	3 / 1
HDMI In / Out	6+1 / 3 (2xMain/Zone2)
AUDIO	
Analogue In / Out	5+1
Digital Optical In / Out	2 / 0
Digital Coaxial In / Out	2 / 0
Multichannel Pre Out	• (11.2)
Subwoofer Out	2 (Independent)
Zone Preout	Zone2/Zone3
7.1 multichannel input	•
Phono MM	•
OTHERS	
M-XPort for RX101	•
Speaker A / B	•
Height Speaker Terminal	Speaker B or Height
Bi-amp drive	• (assignable)
Multi-Room Speaker Terminal	•
Height Speaker Terminal	•
Marantz remote bus	•
Wide Speaker Terminal	•
IR Flasher In	•
Network: (IP-control / update)	• / •
RS232C (control / update)	• / •
USB firmware update	•
DC Triggers	2
Front Inputs: Audio / Composite / HDMI / USB	• / • / • / •
USB Audio / Made for iPod / Works with iPhone	• / • / •
SPECIFICATIONS	
Number of poweramps	9
Power Output per channel	
6 ohm, 1 kHz, 1%, 1ch Drive	200 W
6 ohm, 1 kHz, 0.7%, 2ch Drive	165 W
8 ohm, 20 Hz - 20 kHz, 0.05%, 2ch Drive	125 W
70% Guarantee	•
Audio Signal to Noise Ratio	100 dB
FM Tuner	•
GENERAL	
Available colors: Black / Silver-Gold	• / •
System Remote Control	RC023SR
Pre-programmed / Learnable / LCD Display	• / • / •
Metal Front Panel	•
Power Consumption	710 W
Standby Power Consumption	0.2 W (Standby) 0.5 W (CEC Standby) 2.7 W (Network Standby)
Maximum Dimensions (W x D x H) in mm	440 x 399 x 185
Weight in kg	13.6

* not available in all countries

Design and specifications are subject to change by Marantz without notice.